~~SHIFT REGISTER USING M.I.S. TRANSISTORS~~
~~HAVING THE SAME~~ ~~OF LIKE POLARITY~~

The subject of the present invention is a shift
5   register which can contain just three M.I.S.
transistors and enhancements to this circuit, and in
particular allowing the selection of lines of pixels
from a flat screen.

A flat liquid crystal screen is made up of a
10   number of electro-optical cells arranged in rows and
columns, each controlled by a switching device and
containing two electrodes bordering a liquid crystal
whose optical properties are modified as a function of
the value of the field traversing it. The switching
15   device/electrode/liquid crystal/counter-electrode as-
sembly constitutes a "pixel" (standing for "picture
element"). The addressing of these pixels by the
peripheral control electronics is performed by way of
rows (selection lines) which control the on and off
20   state of the switching devices, and of columns (data
lines) which transmit, when the switching device is on,
a voltage to be applied to the terminals of the
electrodes corresponding to the data signal to be
displayed (gray scale).

25   The electrodes, the switching devices, the rows
and columns are deposited and etched on the same
substrate board, and they constitute the active matrix
of the screen. Advantageously, the peripheral control
circuits, that is to say the selection lines scanner
30   which selects the horizontal lines to be displayed, and
the circuits which control the data lines, are
integrated onto the same substrate board containing the
active matrix and are manufactured at the same time as
the latter.

35   In a flat television or computer screen, the
fact that the number of pixels is very large, that the
spacing of the grid of these pixels is very small, thus
limiting the space available in which to place the
control circuit, and that a large number of selection
40   lines and data lines are [sic] required, compels the

use of the smallest and simplest possible control
circuits so as to achieve a high degree of
manufacturing efficiency. It may moreover be
advantageous to use semiconductor devices as pixel
5 switching devices, with the same conductivity type
throughout the display.

Control of these semiconductor devices can be
undertaken by lines addressed by one or more shift
registers. A register structure such as that
10 represented in Figure 1 provides a partial response to
the requirements stated in the previous paragraph. A
stage 11 of a register contains six transistors Tp, Td,
Ts, Tr, Tl and Tz, and is fed with two clock signals $\Phi1$
and $\Phi3$ at 14 and 15, as well as with two positive
15 sources Vdd and one (relatively) negative source Vss.
The operation of a shift register made up of such
stages is described in detail in International Patent
Application WO 92/15992 filed by Thomson LCD. This
operation relies on the fact that the gate of the
20 transistor Tl which controls the output 13 of the stage
of the register is left floating, and that its
potential therefore follows those of the clock and of
the output through a capacitive effect. This is the
"Boostrap [sic]" effect. This allows, at the desired
25 moment, complete charging of the output 13 to the
highest potential of the clock $\Phi1$. The transistor Tp
allows the gate of the transistor Tl to be precharged
and allows the transistor Td to discharge this gate.

When the stage in question is not selected, its
30 output 13 should remain at the potential Vss. However,
the drain of the transistor Tl is permanently excited
by the clock $\Phi1$, and a consequence of the bootstrap
effect described above is that, with each clock beat Φ
1, the gate of the transistor Tl recovers around half
35 the amplitude of the signals of $\Phi1$ (typically about ten
volts), and the transistor then becomes slightly
passing. It is therefore necessary to switch on the
transistor Tz in order to evacuate the charge from the
node of the output 13 and force this node to the

potential Vss. Likewise, the transistor Td must be kept on over the same period in order to keep the gate voltage of the transistor T1 permanently at the value Vss. The transistors Td and Tz must therefore have a

5 control voltage which is always positive except when the stage is selected. This control voltage at the node P2 is controlled by a R/S (standing for "Reset/Set") toggle made up of two transistors Tr (Reset) and Ts (Set), the dimensions of the transistor Tr being

10 greater than those of the transistor Ts, reset has priority. The clock Φ2 regularly turns on at 15 the set-transistor Ts, taking the node P2 to Vdd, until the input operates the priority reset-transistor Tr at 12 in order to switch off the transistor Tz and allow the

15 transistor T1, which is on, to bias the output node 13.

In short, although the bootstrap effect allows proper charging of the outputs, it is accompanied by stray effects which make it necessary to use three supplementary transistors Tz, Tr and Ts. Another

20 drawback of the solution described in Figure 1 is that the transistors Td and Ts undergo permanent gate stress (that is to say a positive voltage on the gate), a consequence of which may be the drifting of their threshold voltage and in due course a malfunction of

25 the entire device.

The present invention enables these drawbacks to be avoided and proposes simple circuits with three, four or seven transistors, having prolonged lifetimes.

Thus, a first embodiment of the invention

30 relates to a shift register containing a plurality of cascaded three-transistor stages, each one of them being connected up to two clock signals, to the outputs of the preceding stage and the next stage, and characterized in that it includes a first semiconductor

35 output device switching the associated output between high and low values of a first clock signal, this first semiconductor device being controlled by the potential of a first node connected:

· to the output of the preceding stage across a second

semiconductor device controlled by this same preceding output,

· to a negative potential across a third semiconductor device controlled by the output of the next stage,

5 · to a second clock signal across a first capacitance,

· and to the output associated with the stage across a second capacitance.

A second embodiment of the invention relates to a shift register of the same type as the one above, but

10 the stages of which contain seven transistors as well as a first node connected:

· to the output of the preceding stage across a second semiconductor device controlled. by this same preceding output,

15 · to a second clock signal across a first capacitance,

· ~~to the output associated with the stage across a~~ second capacitance, the said output being connected to earth ~~across~~ a third semiconductor device ~~controlled by a second node,~~

20 ~~and to earth across a fourth semiconductor device controlled by the second node,~~

this second node being connected moreover:

· to the output of the preceding stage across a fourth capacitance,

25 ~~to earth across a fifth semiconductor device controlled by the output of the preceding stage,~~

· to the output of the next stage across sixth and seventh clamping transistors mounted in parallel and controlled, one by the second node and the other by

30 the output of the next stage,

· ~~and to that terminal of the third semiconductor device connected to earth, by a capacitance.~~

A third embodiment of the invention relates to a shift register of the same type as those above, but

35 the stages of which contain four transistors as well as a first node connected:

· to the output of the preceding stage across a second semiconductor device controlled by this same preceding output,

to a second clock signal across a first capacitance, ~~to the output associated with the stage across a second~~ capacitance, ~~the said~~ output being connected to earth across a fourth semiconductor device ~~controlled by a second node,~~

5 · to a negative potential across a third semiconductor device controlled by the second node which is moreover connected to the output of the next stage or of the next but one stage.

10 A fourth embodiment of the invention relates to a shift register of the same type as the previous register, but in which the third and fourth semiconductor devices of the stages are controlled respectively by the output of the next stage and by a

15 zero-reset signal.

Finally, a fifth embodiment of the invention relates to a register of the same type as the two previous registers but in which the third and fourth semiconductor devices of the stages are controlled

20 respectively by a clock signal chosen from three and a ~~zero-reset signal.~~

According to important characteristics of the invention, the first and second clock signals are complementary, the first capacitance has a value

25 equivalent to the value of the stray capacitance of the semiconductor output device, and the second capacitance a value substantially greater than that of the stray capacitance of the semiconductor output device.

The present invention also extends to all types

30 of flat active-matrix screen which use peripheral or integrated control circuits.

Moreover, the invention also extends to screens furnished with an enhancement consisting in adding a supplementary conductive column which crosses over the

35 selection lines and is coupled capacitively to each of them in such a way that the corresponding coupling capacitances each have a value close to the sum of the coupling capacitances between a line and the columns which it crosses. This supplementary column can also be

- 6 -

associated with a supplementary conductive line capacitively coupled with it and associated with it across a comparator circuit, this supplementary line being capacitively coupled to each of the columns.

5   The bootstrap effect described above is obtained without any counter-effect. When the stage is idle, there is no longer any positive gate stress and three transistors, one clock and one supply can be discarded as compared with the prior art and, moreover,

10   two embodiments of the invention with seven and four transistors make it possible to work with control signals having an amplitude of 5 to 10 volts below that of the output signals.

        The present invention will be better understood

15   and further advantages will emerge on reading the description which follows, illustrated with the following figures:

· Figure 1 already described represents a stage 11 of a shift register according to the prior art,

20   · Figure 2 represents a first embodiment of a shift register stage according to the invention using three transistors,

· Figures 3a to 3f represent the timing diagram of the elements of the device of Figure 2,

25   · Figure 4 represents a second embodiment of the invention using seven transistors,

· Figures 5a to 5g represent an example of a timing diagram for the elements of the device of Figure 4,

· Figure 6 represents a third embodiment of the

30   invention using four transistors,

· Figure 7 represents a fourth embodiment of the invention also using four transistors,

· Figure 8 represents the timing diagram for the device of Figure 7,

35   · Figure 9 represents a fifth embodiment of the invention using four transistors,

· Figure 10 represents the timing diagram for the device of Figure 9,

· and Figure 11 represents an enhancement to the

present invention.

  In the various figures, the elements having a function which is identical or equivalent from one figure to the other have retained the same references.

5 The various embodiments of the invention which are represented in these figures are shift register stages of integrated drivers controlling liquid crystal screens made with thin-film transistors, but it is obvious that the invention applies to any type of large

10 area electronic circuit made with any semiconductor devices.

  According to the present invention, in Figure 2, there is represented a stage 21 with three transistors T1, Tp and Td, of a shift register controlling a

15 selection line J, and connected at 22 to the preceding line J-1 as well as to the next line J+1 at 30. This circuit is moreover fed with a (relatively) negative source V- and two clocks $\Phi 1$ and $\Phi 2$. The structure of this circuit is described below.

20 This stage is connected at 22 to the preceding line J-1 by the drain of the transistor Tp, a transistor for precharging the gate of the transistor T1 which controls the node D of the output in line J. The gate of the transistor Tp being connected to its

25 drain, this transistor T1 is turned on by the potential of the output line J-1 from the preceding stage at 22. The transistor Tp controls the node G connected to the negative source V- by the transistor Td, itself controlled by the potential of the output line J+1 from

30 the next stage at 30.

  The node D is connected to the source of the transistor T1, to the node G via a capacitance Cb, and to the line J to be selected, whose load which is symbolized electrically by a capacitance Cl.

35 A clock signal $\Phi 1$ is supplied to the drain of the output transistor T1. Between the drain and the gate (node G) of this transistor there is a stray capacitance Cp responsible for the bootstrap effect described above with reference to Figure 1 of the prior

art. According to an important characteristic of the invention, a clock Φ2 which is exactly complementary to the clock Φ1 is connected to the node G via a capacitance C2, with a value equivalent to that of the stray capacitance Cp.

Thus, these stray effects - consequences of the bootstrap effect - are counterbalanced by virtue of the linking of the clock Φ2, the complement of the clock Φ1, with the gate of the transistor T1 via the capacitance C2, with value Ct equivalent to that of Cp. Since the two clocks are exactly complementary they do not give rise to any stray voltage at the node G and hence at the gate of the transistor T1. An equivalent circuit contains a capacitance $C1 = 2 \times Ct$ between the node G and earth 32.

Since such a structure diminishes the bootstrap effect, it is necessary to add a bootstrap capacitance Cb between the source node D and the gate node G so that the voltage of the gate follows a fraction $Cb/(Cb+2 \times Cp)$ of the variations of the source voltage. Thus, in order to attain a bootstrap ratio of 60%, it suffices for Cb to be three times the value of Ct.

Thus, such a circuit preserves the bootstrap effect without its secondary effects described above. The lifetime of the circuit, and hence of the entire device, is prolonged, and the number of transistors required is halved as compared with the prior art. A further advantage of this embodiment of the present invention is that the positive supplies Vdd of the prior art have been discarded. In fact, since the gate and the drain of the precharge transistor Td are connected, when the stage 21 is not selected, the two series transistors Tp and Td carry out the function of the transistor Tz of Figure 1, drawing current from the line J-1 towards the negative voltage V-. The two transistors then have gate-source voltages which are below their threshold voltage, and their channel current is an exponential function of these voltages. This layout results in the gate voltage of the

transistor Tl being around 1 volt below its source
voltage, and this transistor will therefore be blocked
better than in the prior art where the two voltages are
equal. Thus, when a stage of the register according to
5   the invention is not selected, all its transistors have
a gate voltage below their threshold voltages, leading
to minimized fatigue.

The operation of this circuit will be better
understood in the light of the timing diagrams 3a to
10   3f, each of them showing a time scale as abscissa and a
potential as ordinate. When the preceding stage J-1
sends a pulse (Figure 3c) at 22, the precharge
transistor Tp is on and charges the bootstrap
capacitance Cb. The potential of the gate node G
15   (Figure 3d) rises to that of the line J-1 corresponding
to the preceding stage, from which must be deducted
substantially the value of the threshold voltage of the
transistor Tp. The transistor Tl is then on. When the
clock Φ1 rises in turn (Figure 3a), as in the prior art
20   of Figure 1, the output J follows, carrying with it the
gate of the transistor Tl by virtue of the bootstrap
capacitance Cb (Figure 3d). The transistor Tl is then
fully on and the node D and the line J follow the
potential of the clock Φ1 perfectly (Figure 3e) until
25   it falls. At this moment the next line J+1 rises
(Figure 3f) and turns on the transistor Td which
discharges the bootstrap capacitance Cb so that the
transistor Tl is no longer on for the succeeding clock
beats (Figure 3d).

The transistor Td should not be
overdimensioned, so that the transistor Tl remains on
for long enough for the output J to return completely
to zero. As the source of the transistor Tl is slightly
negatively biased, the node G attains a negative
35   voltage when idle, so that the transistor Tl is more
definitely blocked than in the prior art of Figure 1.

Represented in Figure 4 is a second embodiment
of a stage 45 of a shift register according to the
invention. In this figure are again found the three

transistors Tl, Tp and Td, the two inputs J-1 at 22 and J+1 at 30 corresponding respectively to the preceding and next stages, the two opposed clock inputs $\Phi 1$ and $\Phi 2$, the output J of stage 45 on the associated selection line J, as well as the capacitances Cp, C2, Cb and Cl of the embodiment of the invention as described with reference to Figures 2 and 3a to 3g.

According to an important characteristic of the invention, a transistor Tz for resetting the source of the output transistor Tl to zero connects the bootstrap capacitance Cb to earth at 33. The gate of this transistor 47 is controlled by the node Z, connected on one side to the gate of the discharge transistor Td and on the other hand to the next line J+1 via two clamping transistors (gate connected to the source) Th and Tg mounted in parallel head-to-tail, the drains of the two transistors being connected to the sources and the gates being controlled by the sources. That is to say that one, the transistor Tg, is controlled by the node Z and the other, the transistor Th by the line of the next stage J+1. A capacitance Cg is connected on one side to the node Z and on the other to earth at 33.

Moreover, the transistor Td connects the node G to earth, and its gate is controlled by the node Z. The latter is connected to earth across a transistor Tr whose gate is controlled by the node H, that is to say by the output J-1 of the preceding stage. The node Z is furthermore connected to the node H by a capacitance Cc.

The operation of this circuit is essentially the same, in respect of the common parts, as that of the circuit of Figures 2 and 3a to 3f of the previous embodiment of the invention. The enhancement as compared with the latter embodiment is that, when idle, the gates of the transistors Tz and Td, that is to say the node Z, are maintained at the level of their threshold voltage. These transistors are then sufficiently passing to maintain the nodes G and D at the low potential. In this case, the transistor Tp no

longer serves under these conditions to bring the
potential of the outputs to the low point. By virtue of
the two transistors Th and Tg by which it is connected
to the line 30 (the line of the following stage), the
5   potential of the node Z is maintained at the threshold
voltage of the transistors Td and Tz. The node Z will
therefore follow the voltage variations of J+1 with a
voltage lag equivalent to the threshold voltage of the
transistors. Thus, when J+1 rises, the node Z reaches
10 the positive voltage minus the threshold voltage, and
the potentials of the nodes G and D are brought to
zero. The transistors Td and Tz then being fully on.

When the potential of line J+1 returns to zero,
the potential of node Z retains the value of the
15 threshold voltage of the transistors Tp and Tz which
retain some conductivity.

The role of the capacitance Cc is to weaken the
effect of the capacitive couplings across the
transistors Th and Tg to the line J-1, as well as to
20 the source and gate of the transistor Tl.

When idle, the latter has a zero rather than a
negative gate voltage. Its passing state is therefore
better than in the previous solution with three
transistors. The transistor Tz will however override
25 the transistor Tl since it is biased to its conduction
threshold. Hence, the return of the idle outputs to
zero is guaranteed. Another advantage of this solution
with seven transistors is that the output impedance of
the stage 45 is lower than that of the solution with
30 three transistors.

Since the node Z is at relatively high
impedance, the transistor Tr enables the gate voltage
of the transistors Td and Tz to be brought to zero at
the time of precharging, that is to say when the stage
35 is preselected. The blocked transistor Td will enable
the charging of the capacitance Cb to be more complete,
and the blocked transistor Tr will allow the output to
rise to its maximum level. Finally, in order to prevent
the voltage of the node Z from rising when the level of

the output rises, the capacitance Cc should have a value equivalent to that of the gate-drain capacitance of the transistor Tz.

The operation of this circuit will be better understood in the light of the timing diagrams 5a to 5g, each of them showing a time scale as abscissa and a potential as ordinate when the clocks have a smaller swing than that of the outputs. As in the previous embodiment, the clocks Φ1 and Φ2 are opposed (Figures 5a and 5b). The outputs J-1 (Figure 5c), J (Figure 5e) and J+1 (Figure 5f) include three plateaux: the low voltage level of the device when idle, the low level of the clocks when J-1 is active, and the high level of the clocks at selection.

When the stage 45 is selected, that is to say in order than the line J, the output of stage 45, be suitably charged (Figure 5e), the node Z must remain at the level of the threshold voltage of the transistors Td and Tz. But, at this instant, J+1 is at the low level of the clocks (Figure 5f). Bearing in mind the existence of the transistors Th and Tg, the low level of the clocks must therefore not exceed twice the threshold voltage of the transistors.

Thus, this device enhances the present invention insofar as it enables the amplitude of the clocks Φ1 and Φ2 to be reduced by twice the threshold voltage of the transistors, namely, in the example of the amorphous silicon (a-Si) transistors, a value of between 5 and 7 volts.

A third embodiment of the present invention is represented in Figure 6 and, like the previous embodiment, allows the use of input signals of low amplitude. This solution requires just four transistors.

In this Figure 6 are again found the three transistors Tl, Tp and Td, the two inputs J-1 at 22 and J+1 at 30 corresponding to the preceding and next stages respectively, the two opposed clock inputs Φ1 and Φ2, the output J of stage 55 on the associated

selection line J, as well as the capacitances Cp, C2, Cb and C1 of the embodiment of the invention and its first enhancement which were described in the previous figures. The operation of this common part is identical to that described earlier.

This time the enhancement originates from the fact that the gates of the zero-reset transistors Tz and Tp can be connected via the node Z directly to the line J+1 or to the line J+2, that is to say to the output line of the next but one stage. Such a structure makes it possible to dispense with the transistors Tr and Th, as well as with the capacitances Cc and Cg of the previous device. In this case it is necessary for the low clock level which J+2 reaches when J has to return to zero to be sufficient to make the transistors Td and Tz correctly passing (for example 10 volts for amorphous silicon).

This circuit therefore allies simplicity, since it requires just four transistors, and performance since it allows a saving of the order of 10 volts in the control voltages.

A fourth embodiment of the invention is represented by Figure 7. This differs from the previous embodiment of Figure 6 through the fact that the gates of the transistors Td and Tz are no longer common-connected to the succeeding lines. The gate of the transistor Tz is controlled by a reset (re-initializing) signal, the transistor Td is controlled by the next line J+1 and connects the node G to a signal V.

The reset signal controlling the gate of the transistor Tz is a signal consisting of a short pulse of width T1 lagging in phase with respect to the clock signals $\Phi 1$ and $\Phi 2$, and which has a period equal to half that of $\Phi 1$ and $\Phi 2$, as is illustrated by Figure 8. Moreover, the transistor Td whose gate is controlled by the next line J+1 is activated at its source by a signal V with the same frequency as the reset signal controlling the transistor Tz, and with width T2 at the

start of each half-period. This is so as to prevent the transistor Td from discharging the node G too quickly, before the node D, that is to say the line J, has fallen back to the earth level. In fact, when V is
5   positive for the duration T2, the transistor Td cannot discharge the point G, so that T1 can bring the potential of line J (node D) to earth. Thus, each output is earthed at each line addressing time for the short duration T1. This embodiment of the invention may
10 be termed "medium impedance" (low impedance only during the time for which the reset lasts and high impedance for the remainder of the time).

A fifth embodiment of the invention represented in Figure 9 consists in controlling the gate of the
15 transistor Tz with a reset signal and controlling the gate of the transistor Td with a clock signal Φa chosen from three clock signals Φa, Φb and Φc. The source of the transistor Td is maintained at a constant negative potential V-. As Figure 10 shows, each of these clocks
20 consists of a short pulse of duration T3 lagging behind the alternating transitions of $\Phi 1$ and $\Phi 2$, and has a repeat period which is three times that of the reset signal. The three clocks Φa, Φb and Φc are derived from one another through a lag equal to the reset
25 period which corresponds to the line addressing period. This embodiment may be termed "low impedance".

Moreover, the present invention also relates to an enhancement to the present invention with high or medium impedance, making it possible to compensate for
30 the capacitive couplings which exist between the rows and columns of a screen using this type of line driver.

In fact, as shown by Figure 11, which represents a diagrammatic part of a screen containing columns i and rows j controlled by line drivers Dj,
35 when the outputs of a driver Dj of a selection line j are not at low impedance, there are non-negligible capacitive couplings Cij between lines i-1 , i and i+1 and columns j-1, j and j+1, which, when these latter are idle, may give rise to unacceptable voltages

possibly going as far as a change of state of the transistors situated approximately at the intersections of the rows and columns of the active matrix, but not represented in Figure 11.

5   The enhancement to the present invention consists in compensating for these couplings by a column or a bus f capacitively coupled (Cfj) to each of the lines j-1, j and j+1 of the screen. This capacitance should have a value close to the sum of the

10   coupling capacitances Cij between a line and the columns which it crosses. The column f can be activated with each change of polarity on the columns as upon frame reversals or line reversals. Another means of controlling this column f may be to associate

15   therewith, across a comparator 40, a line g itself also coupled capacitively (Cgi) to the columns i-1 , i and i+1 which it crosses. This line g thus makes it possible to detect the couplings with the columns of the screen and to correct the potential of the column f

20   by virtue of the capacitive coupling Cfg between column f and line g. This enhancement applies by preference to the present invention but may be readily extended to all types of flat active-matrix screen controlled via rows and columns by peripheral circuits, either

25   external to or integrated with the screen.

The present invention and its enhancements apply to all shift registers with capacitive output loads, and in particular to control circuit integrated shift registers addressing the lines of a viewing

30   screen. This invention and its enhancements may also be applied in a general way to all large area electronic circuits made with thin-film transistors, as for example fax machine contact scanners or digitizing tablets.